



850 Purchase Order - v4030

X12/V4030/850

Version: 1.1 Final

Author:	Inovis
Publication:	April 1, 2008
Modified:	06/30/2008



Revision History

Date	Version	Revision	Approved By
April 1, 2008	1.0	Initial Publication	Diane Pizzarelli
June 30, 2008	1.1	Added BEG06 Added explanatory notes for special orders.	Diane Pizzarelli

850

Purchase Order

Functional Group=**PO**

This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

User Note:

PLEASE NOTE THAT IN 4030 THE ISA11 NO LONGER CONTAINS THE INTERCHANGE CONTROL STANDARDS IDENTIFIER. IT IS NOW USED TO IDENTIFY THE REPETITION SEPARATOR.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use
0100	ST	Transaction Set Header	M	1			Must use
0200	BEG	Beginning Segment for Purchase Order	M	1			Must use
0500	REF	Reference Identification	O	>1			Used
0600	PER	Administrative Communications Contact	O	3			Used
1300	ITD	Terms of Sale/Deferred Terms of Sale	O	>1			Used
1500	DTM	Date/Time Reference	O	10			Used
LOOP ID - N1					200		
3100	N1	Name	O	1			Used
3200	N2	Additional Name Information	O	2			Used
3300	N3	Address Information	O	2			Used
3400	N4	Geographic Location	O	>1			Used
3600	PER	Administrative Communications Contact	O	>1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					100000	N2/0100L	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
LOOP ID - PID					1000		
0500	PID	Product/Item Description	O	1			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CTT					1	N3/0100L	
0100	CTT	Transaction Totals	O	1		N3/0100	Used
0300	SE	Transaction Set Trailer	M	1			Must use
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

ISA Interchange Control Header

Pos:	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier Description: Code identifying the type of information in the Authorization Information	M	ID	2/2	Must use
		Code Name				
		00 No Authorization Information Present (No Meaningful Information in I02)				
ISA02	I02	Authorization Information Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)	M	AN	10/10	Must use
ISA03	I03	Security Information Qualifier Description: Code identifying the type of information in the Security Information	M	ID	2/2	Must use
		Code Name				
		00 No Security Information Present (No Meaningful Information in I04)				
ISA04	I04	Security Information Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)	M	AN	10/10	Must use
ISA05	I05	Interchange ID Qualifier Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified	M	ID	2/2	Must use
		Code Name				
		01 Duns (Dun & Bradstreet)				
		ZZ Mutually Defined				
ISA06	I06	Interchange Sender ID Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element User Note: <i>Inovis Test: CLPEPBOYS</i> <i>Pep Boys Test: 007914401T</i> <i>Production: 007914401</i>	M	AN	15/15	Must use
ISA07	I05	Interchange ID Qualifier Description: Code indicating the system/method of code structure used to	M	ID	2/2	Must use

		designate the sender or receiver ID element being qualified All valid standard codes are used.				
ISA08	I07	Interchange Receiver ID Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them	M	AN	15/15	Must use
ISA09	I08	Interchange Date Description: Date of the interchange	M	DT	6/6	Must use
ISA10	I09	Interchange Time Description: Time of the interchange	M	TM	4/4	Must use
ISA11	I65	Repetition Separator Description: Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator	M		1/1	Must use
ISA12	I11	Interchange Control Version Number Description: Code specifying the version number of the interchange control segments Code Name 00403 Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1999	M	ID	5/5	Must use
ISA13	I12	Interchange Control Number Description: A control number assigned by the interchange sender	M	N0	9/9	Must use
ISA14	I13	Acknowledgment Requested Description: Code indicating sender's request for an interchange acknowledgment Code Name 1 Interchange Acknowledgment Requested	M	ID	1/1	Must use
ISA15	I14	Usage Indicator Description: Code indicating whether data enclosed by this interchange envelope is test, production or information Code Name P Production Data T Test Data	M	ID	1/1	Must use
ISA16	I15	Component Element Separator Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator	M		1/1	Must use

GS**Functional Group Header**

Pos:	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

To indicate the beginning of a functional group and to provide control information

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code Description: Code identifying a group of application related transaction sets	M	ID	2/2	Must use
		Code Name PO Purchase Order (850)				
GS02	142	Application Sender's Code Description: Code identifying party sending transmission; codes agreed to by trading partners User Note: <i>Inovis Test: CLPEPBOYS</i> <i>Pep Boys Test: 007914401T</i> <i>Production: 007914401</i>	M	AN	2/15	Must use
GS03	124	Application Receiver's Code Description: Code identifying party receiving transmission; codes agreed to by trading partners	M	AN	2/15	Must use
GS04	373	Date Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year	M	DT	8/8	Must use
GS05	337	Time Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)	M	TM	4/8	Must use
GS06	28	Group Control Number Description: Assigned number originated	M	N0	1/9	Must use

		and maintained by the sender				
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
		Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480				
		<u>Code</u>				
		<u>Name</u>				
		X				Accredited Standards Committee X12
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
		Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed				
		<u>Code</u>				
		<u>Name</u>				
		004030				Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1999

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the start of a transaction set and to assign a control number

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition.

Example:

*ST*850*001*

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code Description: Code uniquely identifying a Transaction Set	M	ID	3/3	Must use
		Code Name				
		850 Purchase Order				
ST02	329	Transaction Set Control Number Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M	AN	4/9	Must use

BEG Beginning Segment for Purchase Order

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

Example:

```
BEG*00*NE*N8095301**20080115~
```

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG01	353	Transaction Set Purpose Code Description: Code identifying purpose of transaction set	M	ID	2/2	Must use
		Code Name 00 Original				
BEG02	92	Purchase Order Type Code Description: Code specifying the type of Purchase Order	M	ID	2/2	Must use
		Code Name NE New Order OS Special Order				
BEG03	324	Purchase Order Number Description: Identifying number for Purchase Order assigned by the orderer/purchaser	M	AN	8/8	Must use
BEG05	373	Date Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year	M	DT	8/8	Must use
BEG06	367	Contract Number Description: Contract number User Note: <i>Pep Boys-assigned Vendor Number. Used for Special Orders only.</i>	O	AN	10/10	Used

REF Reference Identification

Pos: 0500	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

To specify identifying information

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

Example:

```
REF*IA*1234567890~
REF*L1**FREE-FORM MESSAGE~
```

User Note:

No REF segments will be sent for Special Orders.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier Description: Code qualifying the Reference Identification	M	ID	2/3	Must use
		Code Name				
		IA Internal Vendor Number				
		L1 Letters or Notes				
REF02	127	Reference Identification Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier	X	AN	1/10	Used
		User Note: <i>Used for vendor number assigned by Pep Boys (DC and Drop Ship only) only when REF01=IA</i>				
REF03	352	Description Description: A free-form description to clarify the related data elements and their content	X	AN	1/60	Used
		User Note: <i>Used for free-form message only when REF01=L1</i>				

PER Administrative Communications Contact

Pos: 0600	Max: 3
Heading - Optional	
Loop: N/A	Elements: 4

User Option (Usage): Used

To identify a person or office to whom administrative communications should be directed

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

Example:

PER*CW*ABC SUPPLY*FX*8005551234~

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code Description: Code identifying the major duty or responsibility of the person or group named	M	ID	2/2	Must use
		Code Name CW Confirmed With				
PER02	93	Name Description: Free-form name	O	AN	1/30	Used
PER03	365	Communication Number Qualifier Description: Code identifying the type of communication number	X	ID	2/2	Used
		Code Name FX Facsimile				
PER04	364	Communication Number Description: Complete communications number including country or area code when applicable	X	AN	1/10	Used

ITD Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: >1
Heading - Optional	
Loop: N/A	Elements: 5

User Option (Usage): Used

To specify terms of sale

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

1. ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

Example:

*ITD*01*3*2**60**90*

User Note:

No ITD Segment will be sent for Special Orders.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD01	336	Terms Type Code Description: Code identifying type of payment terms <u>Code</u> <u>Name</u> 01 Basic	O	ID	2/2	Used
ITD02	333	Terms Basis Date Code Description: Code identifying the beginning of the terms period <u>Code</u> <u>Name</u> 3 Invoice Date	O	ID	1/2	Used
ITD03	338	Terms Discount Percent Description: Terms discount percentage, expressed as a percent, available to the purchaser if an invoice is paid on or before the Terms Discount Due Date	O	R	1/6	Used
ITD05	351	Terms Discount Days Due Description: Number of days in the terms discount period by which payment is due if terms discount is earned	X	N0	1/3	Used
ITD07	386	Terms Net Days Description: Number of days until total invoice amount is due (discount not applicable)	O	N0	1/3	Used

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify pertinent dates and times

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

Example:

```
DTM*002*20080120~
DTM*010*20080115~
DTM*938*20080229~
```

User Note:

002 - Delivery Requested Date - is used for standard orders only.
 010 - Requested Ship Date - is used for standard orders only.
 938 - Order Date - is used for special orders only.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier Description: Code specifying type of date or time, or both date and time	M	ID	3/3	Must use
		Code Name				
		002 Delivery Requested				
		010 Requested Ship				
		938 Order				
DTM02	373	Date Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year	X	DT	8/8	Used

N1**Name**

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

To identify a party by type of organization, name, and code

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

Example:

```
N1*ST*PEP BOYS*92*14011~
```

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code Description: Code identifying an organizational entity, a physical location, property or an individual Code Name ST Ship To	M	ID	2/3	Must use
N102	93	Name Description: Free-form name	X	AN	1/60	Used
N103	66	Identification Code Qualifier Description: Code designating the system/method of code structure used for Identification Code (67) User Note: 92 - Assigned by Buyer - used for standard orders only. ZZ - Mutually Defined - used for special orders only. Code Name 92 Assigned by Buyer or Buyer's Agent ZZ Mutually Defined	X	ID	1/2	Used
N104	67	Identification Code Description: Code identifying a party or other code User Note: Pep Boys Store Number	X	AN	2/5	Used

N2

Additional Name Information

Pos: 3200	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

To specify additional names

Example:

*N2*ATLANTA DIST CNTR~*

User Note:

N2 segment not sent for special orders.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name Description: Free-form name	M	AN	1/60	Must use

N3 Address Information

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

To specify the location of the named party

Example:

*N3*2640 EAST 45TH STREET~*

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information Description: Address information	M	AN	1/55	Must use
N302	166	Address Information Description: Address information	O	AN	1/55	Used

N4 Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To specify the geographic place of the named party

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Example:

N4*LOS ANGELES*CA*90058~

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name Description: Free-form text for city name	O	AN	2/30	Used
N402	156	State or Province Code Description: Code (Standard State/Province) as defined by appropriate government agency	X	ID	2/2	Used
N403	116	Postal Code Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)	O	ID	3/15	Used

PER Administrative Communications Contact

Pos: 3600	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To identify a person or office to whom administrative communications should be directed

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

Example:

```
PER*ZZ**TE*2155551212~
PER*OC**AD*3055551234~
```

User Note:

PER01 qualifier OC and PER03 qualifier AD will be used for special orders only.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code Description: Code identifying the major duty or responsibility of the person or group named	M	ID	2/2	Must use
		Code Name OC Order Contact ZZ Mutually Defined				
PER03	365	Communication Number Qualifier Description: Code identifying the type of communication number	X	ID	2/2	Used
		Code Name AD Delivery Location Phone TE Telephone				
PER04	364	Communication Number Description: Complete communications number including country or area code when applicable	X	AN	1/10	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 13

User Option (Usage): Must use

To specify basic and most frequently used line item data

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Example:

*Standard Order - PO1*001*180*EA***BP*8006747*VP*PF52*UK*03666624066453~
Special Order - PO1*001*1*EA*****VP*PF52***TP*UMF*MD*01~*

User Note:

*PO106/PO107 and PO110/PO111 not sent for special orders.
PO112 thru PO115 not sent for standard orders.*

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification Description: Alphanumeric characters assigned for differentiation within a transaction set	O	AN	1/20	Used
PO102	330	Quantity Ordered Description: Quantity ordered	X	R	1/15	Used
PO103	355	Unit or Basis for Measurement Code Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	O	ID	2/2	Used
		Code Name				
		EA Each				
PO106	235	Product/Service ID Qualifier Description: Code identifying the	X	ID	2/2	Used

			type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>	<u>Name</u>				
		BP	Buyer's Part Number				
PO107	234	Product/Service ID		X	AN	1/10	Used
		Description:	Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier		X	ID	2/2	Used
		Description:	Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>	<u>Name</u>				
		VP	Vendor's (Seller's) Part Number				
PO109	234	Product/Service ID		X	AN	1/20	Used
		Description:	Identifying number for a product or service				
PO110	235	Product/Service ID Qualifier		X	ID	2/2	Used
		Description:	Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>	<u>Name</u>				
		UK	EAN/UCC - 14				
		Description:	Data structure for the 14 digit EAN.UCC (EAN International.Uniform Code Council) Global Trade Identification Number (GTIN)				
PO111	234	Product/Service ID		X	AN	14/14	Used
		Description:	Identifying number for a product or service				
PO112	235	Product/Service ID Qualifier		X	ID	2/2	Used
		Description:	Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>	<u>Name</u>				
		TP	Product Type Code				
PO113	234	Product/Service ID		X	AN	1/48	Used
		Description:	Identifying number for a product or service				
PO114	235	Product/Service ID Qualifier		X	ID	2/2	Used
		Description:	Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>	<u>Name</u>				
		MD	Method of Delivery Code				
PO115	234	Product/Service ID		X	AN	1/48	Used
		Description:	Identifying number for a product or service				
		<u>Code</u>	<u>Name</u>				
		01	Ships in 3 - 5 Business Days				
		02	Ships Next Business Day				
		03	Expedite - 24/48 Hour Guarantee				
		04	Two Day Air				
		05	International Ship				
		06	Your Truck				
		07	Pickup				

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

To describe a product or process in coded or free-form format

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

Example:

*PID*F****PART DESCRIPTION~*

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type Description: Code indicating the format of a description	M	ID	1/1	Must use
		Code Name F Free-form				
PID05	352	Description Description: A free-form description to clarify the related data elements and their content	X	AN	1/25	Used

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

Example:

CTT*5*90~

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items Description: Total number of line items in the transaction set	M	N0	1/6	Must use
CTT02	347	Hash Total Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element. Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. ----- 1855 Hash Total User Note: <i>Total Quantity in Line Items</i>	O	R	1/10	Used

SE**Transaction Set Trailer**

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Comments:

1. SE is the last segment of each transaction set.

Example:

SE*15*001~

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments Description: Total number of segments included in a transaction set including ST and SE segments	M	N0	1/10	Must use
SE02	329	Transaction Set Control Number Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M	AN	4/9	Must use

GE Functional Group Trailer

Pos:	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of a functional group and to provide control information

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element	M	N0	1/6	Must use
GE02	28	Group Control Number Description: Assigned number originated and maintained by the sender	M	N0	1/9	Must use

IEA Interchange Control Trailer

Pos:	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups Description: A count of the number of functional groups included in an interchange	M	N0	1/5	Must use
IEA02	I12	Interchange Control Number Description: A control number assigned by the interchange sender	M	N0	9/9	Must use